

SPECIFICATION COMPARISON BETWEEN FW2-PIRCAM-OUT AND SH-PIRCAM-OUT



FW2-PIRCAM-OUT



SH-PIRCAM-OUT

Part Number	0028552	220059550
Detection and Picture	Quad Element PIR & CMOS Camera	PIR Motion Sensor with Anti-Mask & CMOS camera
Events	Alarm, Tamper, Supervision, Low Bat	Alarm, Anti-Mask, Tamper, Battery Low, Supervision
Communication Protocol	Freewave2™ two-way ISM GFSK with 5 freq. & LBT	
Operating frequencies	868MHz or 916MHz	
Camera sensor	CMOS camera with VGA or QVGA resolution	VGA/QVGA, 16V lux/sec, field of view 90°
Detection Range	Up to 12m	Up to 15m
Installation Height	1.20m	
Pet Immunity	Up to 35 kgs	
Tamper Protection	Front cover opening and wall removal	Cover and wall removal
LED Indication	Red LED indicator for Alarm	Red LED indicator for Alarm and Trouble state
Battery	Two 3V Lithium battery D Size	4 x Lithium batteries 1.5V AA
Battery Life	Up to 3 years	Up to 5 years
Current Consumption	Average 38mA	Average 140 uA
Transmission Range	400m open space	500m open space
Operating Temperature	-25°C to +55°C	-40°C to +55°C
IP Protection	IP 65	
Accessories	Batteries and Wall bracket supplied	Batteries, Wall bracket and water levels supplied
Dimensions	135mm x 75mm x 70mm	218mm x 75mm x 87mm
Weight	400 grs	400 grs
Compliance	CE	